

25 Years of Manufacturing Excellence

# Zeta<sup>®</sup>

ALARM SYSTEMS



*mkII* PROTOCOL

## Standard Protocol / MKII Protocol Device Compatibility

# Standard Protocol / MkII Protocol Device Compatibility













In April 2013 the Zeta Alarm Systems range of Addressable fire alarm Equipment will be migrating to our new Fyreye MK II Protocol. The table below shows which devices will work with the old protocol, and which will work with the new protocol.

On the **SIMPLICITY PLUS** panel, software versions Controller **1.A - R8687** or later fully support the Fyreye MKII Protocol









To Check Software version, go to Configuration Menu 2, select Configure system, select Misc, then select Version.

	Device	Standard Protocol	MKII Protocol
<b>Detectors</b>			
	FEAx2000	✓	✗
	FEAxE2000	✓	✗
	MKII-Axx	✗	✓
<b>Interfaces</b>			
	ZIU / ZIOU / ZSCC / ZIOU/230	✓	✗
	ZTSM	✓	✗
	ZTA-DH	✓	✗
	ZAI-MI	✓ (Factory selectable)	✓
	ZAIO-MI	✓ (Factory selectable)	✓
	ZASC-MI	✓ (Factory selectable)	✓
	ZAZM-MI	✓ (Factory selectable)	✓

# Standard Protocol / MkII Protocol Device Compatibility

	Device	Standard Protocol	MKII Protocol
	ZIOU/I-230	✓	✗
	ZAI0I/230	✗	✓
	SMM/S	✗	✓
	SMM/C	✗	✓
	SMM/B	✗	✓
Call Points			
	ZT-CP2/AD	✓	✗
	ZT-CP3/AD	✓ (User selectable)	✓
Sounders			
	ZAMD / ZAMDF	✓	✗
	ZAMT / ZAMTF	✓	✗
	ZAS2/xxx	✓	✗
	ZTA-CSB / ZTA-CSFIB	✓	✗
	SM-ASB	✓	✗

# Standard Protocol / MkII Protocol Device Compatibility

	Device	Standard Protocol	MKII Protocol
	MKII-AMDx	✓ (User selectable)	✓
	MKII-AMTx	✓ (User selectable)	✓
	MKII-AXTx	✗	✓
	MKII-SSB	✗	✓
	ID2-SFB	✗	✓
Remote Indicators			
	ZTA-LE2	✓	✗
	ZTA-LE3	✓	✗
	MKII-ARL/C	✓ (Factory selectable)	✓
	MKII-ARL/W	✓ (Factory selectable)	✓